

Vision120 DMX Decoder

120V, 4 CHANNELS

GM Lighting®



GAIN ULTIMATE LIGHTING CONTROL & DESIGN LIMITLESS LIGHT COMBINATIONS

DMX decoder allows you to change and modify your LED installation into lighting sequences and gain independent control between sections with 100% to 1% dimming or other lighting effects. It works with 120V LED tape including Vision120 providing reliable lighting control.

Our DMX Decoder supports DMX512/RDM signal for bidirectional communication while achieving remote management of reading and writing DMX addresses.

DMX DECODER

- 120VAC
- 100% to 1% dimming
- 4-channels: Red, Green, Blue, White
- Current Load: Max. 6A
- Max Output Power: 720W total (180W per channel)
- User-friendly digital display
- DMX address settable from 1 to 512
- Works with any DMX system
- Self-testing
- Wet location - IP67
- Works with RGBW tape including Vision120 RGBW
- FCC, ETL, CE, RoHS, cRUus

DMX REMOTE CONTROLLER

- Touch sensitive
- 10 preset modes
- Thousands of color options
- 4-channels: Red, Green, Blue, White
- Control up to 3 zones
- Dimming / Brightness / ON/OFF control options
- Fits standard junction box



GM Lighting®

©2021 GM LIGHTING, LLC • www.gmlighting.net • Specifications subject to change without notice
18700 Ridgeland Ave., Tinley Park, IL 60477 • Toll-Free: (866) 671-0811 FAX: (708) 478-2640 • tech@gmlighting.net

Vision120 DMX Decoder

120V, 4 CHANNELS

GM Lighting®



ORDERING INFORMATION

Model	Description
V120-RGBW-DMX	V120RGBW DMX Decoder 1.5A x 4CH 6A

Note: Includes 4x wire splice connectors and plugs

ACCESSORIES

Model	Description
RGBW-DMX-WC	RGBW DMX512 Wall Controller
SJTW-2W	SJTW-2W wire / per ft.
SJTW-3W	SJTW-3W wire / per ft.
SJTW-5W	SJTW-5W wire / per ft.

APPLICATIONS

- ▶ Hotels
- ▶ Bars & Nightclubs
- ▶ Themed Applications
- ▶ Decorative Lighting
- ▶ Buildings
- ▶ Bridges
- ▶ Commercial Offices
- ▶ Hallways
- ▶ Concerts
- ▶ Theaters
- ▶ Staging
- ▶ Restaurants
- ▶ Retail
- ▶ Hospitality

